

# Touch Driver Install Manual

## SPT-4700

(Version 1.0)

www.sam4s.com

Revision A (Aug 17, 2012)



### Contents

* Touch Driver Install Procedure	3
* Calibration of Touch Screen	9
* Select mouse right click function	12



#### \* Touch Driver Install Procedure

1) Run 'SWxxxxx\_TETouch\_x.x.x.exe' file.

(X The file version of touch driver can change without notice.)



2) Click 'Next' button.

Elo Touchscreen Setup ( 🔛 )
Pick the default language for the Elo Touchscreen Driver package.         All Elo touchscreen applications will be displayed in the language selected below.         Default       T
[Next > ] Cancel



3) Check the 'Install Serial Touchscreen Drivers' box. And click 'Next' button.



4) Agree with license agreement. Click 'Yes' button.

Elo Touchscreen Setup (Tarti)	×
License Agreement Please read the following license agreement carefully. Press the PAGE DOWN key to see the rest of the agreement.	
End-User License Agreement	
PRODUCT LICENSE AND LIMITED WARRANTY. IMPORTANT READ CAREFULLY: This Elo TouchSystems End-User License Agreement ("EULA") is a legal	
Do you accept the terms of the preceding license agreement? If you choose No, you will not have full touchmonitor functionality and setup will close. To have full functionallity you must accept the license agreement.	
< Back Yes No	



#### 5) Click 'Next' button.



6) Check the serial port 'COM5' for touch screen. Click 'Next' button.

Elo Touchscreen Setup (	$\mathbf{X}$
TOUCHSYSTEMS	Choose the COM ports from the list below to use with your touchmonitors. All COM ports reported by your system are listed.
	< Back Next > Cancel



7) Confirm the serial port is 'COM5'. And click 'Next' button.



8) If the setup is completed, click 'Finish' button.

Elo Touchscreen Setup (	
<b>BO</b> TOUCHSYSTEMS	Setup Complete Setup has finished installing the Elo touchscreen drivers and components. You can choose to calibrate your Elo Touchscreen monitors after setup finishes.
IIIII	<ul> <li>Calibrate Elo Touchscreen monitors.</li> <li>View Readme.</li> </ul>
	Click Finish to exit Setup.
	< Back Finish



9) Calibration procedure will be started. Press the center of red circle more than 2 seconds.

Touch targets from position of normal use

10) When the red circle appears in other area, press the center of red circle more than 2 seconds.

Touch targets from position of normal use	



11) When the red circle appears in other area, press the center of red circle more than 2 seconds.



12) Click the green box to finish the calibration procedure.





#### \* Calibration of Touch Screen

1) Click the 'elo icon' on tray area in Windows. And select 'Align...' memu.

🗟 Elo Touchscreen Propertie	25
🖳 Align	
R Elo Right Mouse Button Tool	
Disable Touch	
Readme	
Users Manual	
www.elotouch.com	
🗙 Exit	
	🧐 🦉 🤤 😵 8:59 PM

2) Calibration procedure will be started. Press the center of red circle more than 2 seconds.

Touch targets from position of normal use	



3) When the red circle appears in other area, press the center of red circle more than 2 seconds.



4) When the red circle appears in other area, press the center of red circle more than 2 seconds.

Touch targets from position of normal use	



5) Click the green box to finish the calibration procedure.





#### \* Using mouse right click function

If you press the same point on desktop more than 2 seconds, the pop-up will be displayed. It is similar function with right-click of mouse. Refer to below steps to select "using mouse right-click function".

1) Click the 'elo icon' on tray area in Windows. And select 'Elo Touchscreen Properties' on the menu.



2) Select 'Properties 1' tab.





3) Click 'Advanced' button.

Elo Touchscreen Properties	? 🔀	
General Mode Sound Properties 1 About		
Windows monitor number: 1	$\checkmark$	
Touchscreen type: AccuTouch		
Connection Port: COM5		
Controller model: 2216 [2.1 - 0.0]		
Controller Status: Working properly		
Controller Serial Number: UN000000		
Identify Align Monitor Advanced		
Ok Cancel Apply	Help	

4) Check the 'Enable right click on hold' box.

Advanced	×
Touch	
Options	Edge acceleration tool
Disable touch	Enable cursor edge acceleration
	Apply> button will act on all touch monitors
Show right mouse button tool	Customize
Right click on hold feature	
Enable right click on hold	Right click area
Apply to all touchscreens	
Right click delay	
	Ok Cancel Apply



5) Save the current change to click '**Ok**' button.



6) Finish the dialog to click '**Ok**' button.

Elo Touchscreen Properties		? 👌	8
General Mode Sound Properties 1 At	oout		1
Windows monitor number:		1	
Touchscreen type:	Aci	cuTouch	
Connection Port:	(	COM5	
Controller model:	2216	[2.1 - 0.0]	
Controller Status:	Worki	ing properly	
Controller Serial Number:	UN	1000000	
Id. Align	entify onitor	Advanced	
Ok	Cancel	Apply Help	